

Nomenclature *P S S* Part List
Amplificateurs Type : 8-C4 Amplifiers Date : 09-08-1999

Reference	Valeur - Value	Reference	Valeur - Value
C 1, C 12,	470 µF 16V	R 2, R 5, R 6, R 8	47 000 Ω
C 24, C 30, C31, C41	1 000 µF 16V	R 3	3 300 Ω
C8,C11,C18,C19,C32,C33,C34	47 µF 63V	R 10(2W), R 28(2W), R 31	680 Ω
C 3, C 4, C 5, C 6, C 13	4,7 µF 63V	R 12, R 24, R 25, R 29	18 000 Ω
C 15, C 22, C 27	39 pF	R13, R 38	47 Ω
C 2, C 10, C 17	270 pF	R 21, R 30	1 000 Ω - 2 W
C 25	560 pF	R 22, R 40, R 42, R 43	120 Ω
C 9, C 20	10 nF	R 23	10 Ω - 3 W
C 7, C 14, C 21, C 28, C 29	220 nF	R 26, R 56	8 200 Ω
C 16, C 23, C 26	47 nF	R 39, R 57	22 000 Ω
CTN 1&2 - NTC 1&2 (3%)	100 000 Ω	R 41	470 Ω
CI 1, CI 2	UA 741	R 44, R 46, R 47, R 49, R 51	1 800 Ω
D7, D 10, D 29, D 30, D 32,D33	BY 550-600V5A	R 45, R 52, R 53	39 000 Ω
D 2, D 3, D 6, D 9, D 11, D 12, D13, D 14, D 15, D 16, D 19 , D 22, D 23, D 24, D 25, D 26, D 27, D 28, D 31, D Led	1N 4004	R 48	15 000 Ω
D 18, D 20 (3mm Led)	Verte/Green	R 50	33 000 Ω
D 4, D 21 (3mm Led)	Rouge/Red	R 54, R 55	2 700 Ω
D 17 (3mm Led)	Jaune/Yellow	R 58, R 61, R 62	82 000 Ω
T 8, T 23, T 24	MPSA 06	R 59	6 200 Ω
T 9, T 10, T 11, T 20, T 21	MPSA 56	R 60	10 000 Ω
T 22	TIP 41 C	L 1	0.1 mH
T 18	TIP 50	K1	10 A relais/relay
Régulateur - Fan Regulator	LM317T	D 1, D 5 (Zener)	15 V

All transistors are MOTOROLA brand - Tous les transistors sont de marque MOTOROLA

Reference	SAP 2150	SAP 2200	SAP 2300 / SAP 2400	SAP 2600	SAP 2800
C 35, C 36, C 37	4700 µF 63V	4700 µF 63V	2 x 4700 µF 63V/80V	2x4700 µF 80V	3x4700 µF 100V
C 38, C 39, C 40	4700 µF 63V	4700 µF 63V	2 x 4700 µF 63V/80V	2x4700 µF 80V	3x4700 µF 100V
R 1, R 11	33 000 Ω	39 000 Ω	47 000 Ω/56 000 Ω	82 000 Ω	100 000 Ω
R 4	1 800 Ω	1 800 Ω	2 700 Ω	2 700 Ω	2 700 Ω
R 7	3 300 Ω	3 300 Ω	3 300 Ω	4 700 Ω	6 800 Ω
R 9	68 Ω	68 Ω	68Ω (2300)/47Ω (2400)	15 Ω	15 Ω
R 20	22 000 Ω	24 000 Ω	27 K (2300)/33 K (2400)	39 000 Ω	56 000 Ω
R 27	470 Ω	470 Ω	330 Ω	330 Ω	330 Ω
R 55	10 000 Ω	12 000 Ω	15 K (2300)/18 K (2400)	18 000 Ω	22 000 Ω
T 1	TIP 41 C	TIP 41 C	MJE 13007	MJE 13007	MJE 13007
T 19	TIP 42 C	TIP 42 C	MJE 5852	MJE 5852	MJE 5852
T 2 - T 7	1 x MJ 15003	2 x MJ15003	3 x MJ 15003/15024	4 x MJ 15024	6 x MJ 15024
T 12 - T 17	1 x MJ 15003	2 x MJ15003	3 x MJ 15003/15024	4 x MJ 15024	6 x MJ 15024
R 14 - R 19	1 x 0,22 Ω 3W	2 x 0,33 Ω 3W	3 x 0,33 Ω 3W	4 x 0,33 Ω 3W	6 x 0,33 Ω 3W
R 32 - R 37	1 x 0,22 Ω 3W	2 x 0,33 Ω 3W	3 x 0,33 Ω 3W	4 x 0,33 Ω 3W	6 x 0,33 Ω 3W
D 8 (Zener)	30 V	33 V	36 V(2300)/ 39 V(2400)	42 V	51 V
F 2	3,15 A	3,15 A	4 A(2300) - 5 A(2400)	6,3 A	6,3 A
F 3	rapide/fast	rapide/fast	rapide/fast	rapide/fast	rapide/fast

Entrepôts-Warehouse : ZI Sud, avenue Pierre Morin, route de Fourques 30300 Beaucaire, France

Siège Social-Registered Office : 37 avenue Pierre Sémard 84000 Avignon, France

RCS AVIGNON 93 B 440 - SIRET 391 736 576 00011 - APE 516J SARL au capital de 80 000 F

Tél. : 33 466 593 955 Fax : 33 466 590 636